

Moderated Degradation Enhancement of Lateral Pnp Transistors Due to Measurement Bias

15 May 1999

Prepared by

S. C. WITCZAK, R. C. LACOE, and D. C. MAYER
Electronics Technology Center
Technology Operations
The Aerospace Corporation

R. D. SCHRIMPF, H. J. BARNABY, and K. F. GALLOWAY
Department of Electrical and Computer Engineering
Vanderbilt University
Nashville, TN 37235

R. L. PEASE
RLP Research, Inc.,
Albuquerque, NM 87122-1138

and

D. M. FLEETWOOD
Sandia National Laboratories
Albuquerque, NM 87185-1083

Prepared for

SPACE AND MISSILE SYSTEMS CENTER
AIR FORCE MATERIEL COMMAND
2430 E. El Segundo Boulevard
Los Angeles Air Force Base, CA 90245

Engineering and Technology Group

APPROVED FOR PUBLIC RELEASE;
DISTRIBUTION UNLIMITED



**THE AEROSPACE
CORPORATION**

El Segundo, California


DTIC QUALITY INSPECTED 4

19990603 162

This report was submitted by The Aerospace Corporation, El Segundo, CA 90245-4691, under Contract No. F04701-93-C-0094 with the Space and Missile Systems Center, 2430 E. El Segundo Blvd., Suite 6037, Los Angeles AFB, CA 90245-4687. It was reviewed and approved for The Aerospace Corporation by R. P. Frueholz, Principal Director, Electronics Technology Center. Michael Zambrana was the project officer for the Mission-Oriented Investigation and Experimentation Program (MOIE) program.

This report has been reviewed by the Public Affairs Office (PAS) and is releasable to the National Technical Information Service (NTIS). At NTIS, it will be available to the general public, including foreign nationals.

This technical report has been reviewed and is approved for publication. Publication of this report does not constitute Air Force approval of the report's findings or conclusions. It is published only for the exchange and stimulation of ideas.

A handwritten signature in cursive script, reading "Michael S. Zambrana". The signature is written in dark ink and is positioned above a horizontal line.

Michael Zambrana
SMC/AXE

REPORT DOCUMENTATION PAGE			Form Approved OMB No. 0704-0188	
Public reporting burden for this collection of information is estimated to average 1 hour per response, including the time for reviewing instructions, searching existing data sources, gathering and maintaining the data needed, and completing and reviewing the collection of information. Send comments regarding this burden estimate or any other aspect of this collection of information, including suggestions for reducing this burden to Washington Headquarters Services, Directorate for Information Operations and Reports, 1215 Jefferson Davis Highway, Suite 1204, Arlington, VA 22202-4302, and to the Office of Management and Budget, Paperwork Reduction Project (0704-0188), Washington, DC 20503.				
1. AGENCY USE ONLY (Leave blank)		2. REPORT DATE 15 May 1999		3. REPORT TYPE AND DATES COVERED
4. TITLE AND SUBTITLE Moderated Degradation Enhancement of Lateral pnp Transistors Due to Measurement Bias			5. FUNDING NUMBERS F04701-93-C-0094	
6. AUTHOR(S) Witczak, S.C., Lacoe, R. C., and Mayer, D. C., The Aerospace Corporation; Schrimpf, R. D., Barnaby, H. J., and Galloway, K. F., Vanderbilt University; and Fleetwood, D. M., Sandia National Laboratories.				
7. PERFORMING ORGANIZATION NAME(S) AND ADDRESS(ES) The Aerospace Corporation Technology Operations El Segundo, CA 90245-4691			8. PERFORMING ORGANIZATION REPORT NUMBER TR-99(8555)-1	
9. SPONSORING/MONITORING AGENCY NAME(S) AND ADDRESS(ES) Space and Missile Systems Center Air Force Materiel Command 2430 E. El Segundo Blvd. Los Angeles Air Force Base, CA 90245			10. SPONSORING/MONITORING AGENCY REPORT NUMBER SMC-TR-99-19	
11. SUPPLEMENTARY NOTES				
12a. DISTRIBUTION/AVAILABILITY STATEMENT Approved for public release; distribution unlimited			12b. DISTRIBUTION CODE	
13. ABSTRACT (Maximum 200 words) Enhanced low-dose-rate gain degradation of ADI RF25 lateral pnp transistors is examined as a function of the bias at which the gain is measured. Degradation enhancement at low dose rates diminishes rapidly with increasing measurement bias between the emitter and the base. Device simulations reveal that interface trap charging, field effects from oxide trapped charge and emitter metallization, base series resistance and high-level carrier injection all contribute to this behavior. As a practical consequence, accelerated hardness assurance tests of this device require higher irradiation temperatures or larger design margins for low power applications.				
14. SUBJECT TERMS Design margins Enhanced low-dose-rate gain degradation Hardness assurance		Interface trap Lateral pnp transistors Measurement bias Oxide trapped charge		15. NUMBER OF PAGES 9
				16. PRICE CODE
17. SECURITY CLASSIFICATION OF REPORT Unclassified	18. SECURITY CLASSIFICATION OF THIS PAGE Unclassified	19. SECURITY CLASSIFICATION OF ABSTRACT Unclassified	20. LIMITATION OF ABSTRACT	

Moderated Degradation Enhancement of Lateral pnp Transistors Due to Measurement Bias

S. C. Witczak, *Member, IEEE*, R. D. Schrimpf, *Senior Member, IEEE*, H. J. Barnaby, *Student Member, IEEE*,
R. C. Lacoe, *Member, IEEE*, D. C. Mayer, *Senior Member, IEEE*, K. F. Galloway, *Fellow, IEEE*,
R. L. Pease, *Senior Member, IEEE*, and D. M. Fleetwood, *Fellow, IEEE*

Abstract

Enhanced low-dose-rate gain degradation of ADI RF25 lateral pnp transistors is examined as a function of the bias at which the gain is measured. Degradation enhancement at low dose rates diminishes rapidly with increasing measurement bias between the emitter and the base. Device simulations reveal that interface trap charging, field effects from oxide trapped charge and emitter metallization, base series resistance and high-level carrier injection all contribute to this behavior. As a practical consequence, accelerated hardness assurance tests of this device require higher irradiation temperatures or larger design margins for low power applications.

I. INTRODUCTION

Radiation-induced degradation of many types of bipolar transistors[1,2] and circuits[3] is more severe following low dose rate exposure than following high dose rate exposure. Since microelectronics devices in space are generally subjected to low dose rate irradiation, this complicates the hardness assurance testing of linear circuits and can lead to an overestimation of device lifetimes in space. Of the various approaches tried for hardness assurance testing, the most promising has been high dose rate irradiation at elevated temperature with some measure of design margin to account for in situ annealing[1,2].

Due to their keen sensitivity to radiation, lateral pnp transistors have been the focus of much of the recent work in this area. Ionizing radiation degrades the current gain of lateral pnp transistors primarily by introducing interface traps into the oxide overlying the emitter-base junction[4]. The interface traps increase surface recombination in the base by acting as generation-recombination centers. Conversely, radiation-induced net positive oxide trapped charge can moderate gain degradation as it accumulates the surface of the n-type

base. Since recombination is at a maximum when the concentrations of conduction electrons and holes are equal, positive oxide trapped charge reduces recombination in the base by creating an imbalance in carrier concentrations near the surface.

The amount of design margin required to bound low-dose-rate gain degradation of bipolar transistors is known to depend on total dose[2], irradiation temperature[1,2], device geometry[1], irradiation bias[3] and the dose rate at which testing is performed[5]. In this work, we report that the amount of design margin required to bound radiation-induced gain degradation of lateral pnp transistors also depends on the bias at which the gain is measured. This dependence results from a moderation in low-dose-rate degradation enhancement as the emitter-to-base bias is increased. Mechanisms contributing to this behavior include interface trap charging, field effects from oxide trapped charge and emitter metallization, base series resistance and high-level carrier injection.

II. EXPERIMENT

This work draws on an extensive data set introduced elsewhere[1,2] that relates gain degradation of the Analog Devices RF25 lateral pnp transistor to dose rate and irradiation temperature. This device is fabricated in a Si bipolar process with a highly doped emitter ($\sim 9 \times 10^{19} \text{ cm}^{-3}$) and a base oxide thickness of 570 nm[6]. All irradiations were performed using a ^{60}Co γ -source with the device terminals grounded. Lids on the device packages were removed to avoid dose enhancement from photon scattering[7], and Pb-Al shields were used to filter low energy photons and electrons. Further details concerning the experimental procedure are provided elsewhere[1].


A typical example of the effect of dose rate on excess base current is shown in Fig. 1(a)[1], where excess base current is defined as the increase in base current due to radiation exposure. The excess base current is plotted as a function of emitter-to-base voltage for devices irradiated to 20 krad(Si) at four dose rates between 0.001 and 294 rad(Si)/s. Base recombination increases monotonically with decreasing dose rate for any emitter-to-base voltage examined. However, the magnitude of this increase diminishes rapidly with increasing bias. Furthermore, the slope of the excess base current characteristics at any given dose rate decreases with bias. This

S. C. Witczak, R. C. Lacoe and D. C. Mayer are with the Electronics Technology Center, The Aerospace Corporation, Los Angeles, CA 90009-2957 USA.


R. D. Schrimpf, H. J. Barnaby and K. F. Galloway are with the Department of Electrical and Computer Engineering, Vanderbilt University, Nashville, TN 37235 USA.

R. L. Pease is with RLP Research, Inc., Albuquerque, NM 87122-1138 USA.


D. M. Fleetwood is with Department 1727, Sandia National Laboratories, Albuquerque, NM 87185-1083 USA.




(a)



(a)



(b)



(b)

Fig. 1. Effect of (a) emitter-to-base voltage on excess base current, where dose rate is a parameter (after [1]), and (b) dose rate on excess base current, where emitter-to-base voltage is a parameter. The sensitivity of excess base current to dose rate diminishes with increasing measurement bias between the emitter and the base.

dependence on measurement bias is illustrated more clearly in Fig. 1(b), where excess base current, normalized by its value at 294 rad(Si), is plotted as a function of dose rate for four emitter-to-base voltages between 0.5 and 0.8 V. The ratio of excess base currents at the extreme dose rates increases from approximately six at 0.8 V to more than 30 at 0.5 V.

In Fig. 2(a), representative excess base current characteristics are shown for lateral pnp devices irradiated to 20 krad(Si) at four temperatures between 25 and 135°C[1], where the dose rate is fixed at 294 rad(Si)/s. For any emitter-to-base voltage examined, degradation increases monotonically with temperature. However, similarly to the case for dose rate, the amount of degradation enhancement dimin-

Fig. 2. Effect of (a) emitter-to-base voltage on excess base current, where irradiation temperature is a parameter (after [1]), and (b) irradiation temperature on excess base current, where emitter-to-base voltage is a parameter. The sensitivity of excess base current to irradiation temperature diminishes with increasing measurement bias between the emitter and the base.

ishes rapidly with increasing bias. This result is illustrated more clearly in Fig. 2(b), where normalized excess base current is plotted as a function of irradiation temperature for four emitter-to-base voltages between 0.5 and 0.8 V. The enhancement in degradation due to temperature is moderated by in situ annealing such that a distinct peak in the excess base current occurs for a given bias[1,2,8]. This peak moves to lower irradiation temperatures with increasing bias. The factor by which excess base current is maximally enhanced increases from less than five at 0.8 V to approximately 23 at 0.5 V. Qualitatively similar trends in the measurement bias dependence of degradation enhancement were observed at other total doses examined through 200 krad(Si).

III. MECHANISMS

A. Oxide Trapped Charge

Excess base current in the lateral pnp transistor results primarily from surface recombination within the emitter-base depletion region. The amount of excess base current flowing at the Si surface is obtained from

$$\Delta I_B = q \int_S U dS, \quad (1)$$

where q is the electronic charge, U is the recombination rate per unit area, and S is the surface area over which recombination takes place. The rate of recombination typically is at a maximum near the emitter-base metallurgical junction, where the carrier concentrations are comparable.

When the surface recombination is formulated from Shockley-Read-Hall recombination statistics[9], integration of (1) yields a bias dependence for excess base current that can be approximated by[4]

$$\Delta I_B \propto \exp \left[\frac{(V_{EB} - V_{acc})}{mV_{th}} \right], \quad (2)$$

where $V_{th} = kT/q$ is the thermal voltage, V_{EB} is the applied emitter-to-base voltage, V_{acc} represents the potential drop across the accumulation layer in the neutral base, and m is defined as the ideality factor. Recombination far from the emitter-base junction contributes an ideality factor of one. For recombination occurring at the maximum rate (near the emitter-base junction), an ideality factor greater than one results. The excess base current, therefore, exhibits a weaker dependence on applied bias when the function U is more sharply peaked near the emitter-base junction.

In Fig. 3, recombination rates along the Si surface are shown for several densities of positive oxide trapped charge.




Fig. 3. Effect of positive oxide trapped charge on the surface recombination rate near the emitter-base junction. Positive oxide trapped charge moderates recombination at the base surface while reducing the emitter-base depletion width.

The recombination rates were obtained from two-dimensional computer simulations[10] of the test device and are normalized by the peak rate for constant values of surface recombination velocity and emitter-to-base voltage. Negative abscissas in the figure correspond to locations within the emitter, whereas positive values are located within the base. Positive oxide trapped charge reduces both the emitter-base depletion width and recombination in the neutral base by increasing the difference in carrier concentrations near the base surface. Since reduced recombination in the neutral base leads to a larger ideality factor, the enhancement in excess base current at low dose rates is reduced with increasing emitter-to-base voltage.

B. Interface Trapped Charge

Radiation-induced changes in the surface recombination rate are determined by the sum of bulk oxide trapped charge and charged interface traps. As shown in Figs. 4(a) and 4(b), the net charge contributed by interface traps varies with emitter-to-base bias. The conduction and valence band edges are represented by E_c and E_v , respectively, and E_i denotes the intrinsic energy. The Fermi energy, E_F , indicates the energy below which most of the interface traps are occupied at thermal equilibrium. Under forward bias, the trap occupancies are implied by an effective Fermi energy, F_{eff} , defined as the mean of the carrier quasi-Fermi energies, F_N and F_P .




Fig. 4. Energy band diagram for the emitter-base junction under (a) thermal equilibrium and (b) forward bias. A forward bias moderates carrier recombination along the surface by charging interface traps positive in the base and negative in the emitter.

Under forward bias, the quasi-Fermi energies split by an amount proportional to the applied bias, such that F_N increases in the emitter, and F_p decreases in the base[11]. Some of the interface traps in the base become more positively charged as they emit electrons (or capture holes), while some of the interface traps in the emitter become more negatively charged as they capture electrons (or emit holes). The additional charge above the base moderates base recombination by complementing positive charge trapped in the oxide bulk. The negative charge above the emitter further reduces recombination by mitigating depletion of the emitter. Since the amount of interfacial charge trapping increases with bias, the excess base current characteristics tend to fall off at large biases. Because the doping concentrations in the regions differ, the impact of interface trapped charge on recombination is greater in the base than in the emitter.

C. Emitter Metallization

In most bipolar devices, the emitter metallization covers the base oxide over a portion of the emitter-base depletion region. This overlap functions as a field plate similar to a gate electrode in an metal-oxide-silicon capacitor[12]. As the emitter-base junction is forward biased, charge added to the metal layer reduces the region of high recombination in the underlying depletion region while increasing the potential drop across the accumulated neutral base (V_{acc} in (2)). The excess base current, therefore, is reduced to a value below that which would exist without the presence of the field plate. Since the relative reduction increases with the amount of charge on the field plate, the excess base current characteristics are stretched out for large emitter-to-base voltages. The effects of the field plate and positive oxide trapped charge are conceptually the same; that is, each acts to moderate the effect of near-midgap interface traps by increasing the surface potential in the Si.

D. High-Level Injection and Base Series Resistance

At large forward currents, such that the number of minority carriers injected into the base approaches the majority carrier concentration, non-negligible electric-fields can result in significant ohmic drops across the bulk emitter and base regions[11]. The amount of potential drop increases with current so as to limit further injection of carriers. Since the rate of recombination in the depletion region depends on the concentration of injected carriers, excess base current increases more slowly with emitter-to-base voltage at large levels of current. Sufficiently high-level injection can yield an ideality factor that approaches two.

Base series resistance also contributes to the convergence of excess base current at large biases. An appreciable distributed resistance generally is present in the quasi-neutral

region of the base[11]. This resistance often is significant in lateral pnp transistors due to the separation of the base electrode from the device active region. Since majority carriers in the base must flow into the active area to facilitate recombination and back-injection into the emitter, the applied emitter-to-base voltage is divided across the emitter-base depletion region and the base bulk. The metal-to-silicon contact at the base terminal likewise behaves like a small resistor that adds to the voltage drop. The effect of series resistance is represented in (2) by expressing the junction voltage as $V_{EB} - V_{acc} - I_B R_B$, where $I_B R_B$ represents the potential drop across the base.

IV. HARDNESS ASSURANCE IMPLICATIONS

Fig. 5 illustrates the relationship between irradiation temperature and design margin required to bound low dose rate degradation of the test device at 20 krad(Si), where emitter-to-base voltage is a parameter. The figure was constructed by comparing excess base currents obtained at 294 rad(Si)/s and elevated temperatures to those acquired at 0.001 rad(Si)/s. The ordinates represent safety factors by which the high-temperature data must be multiplied in order to approximate the low dose rate response. Because gain degradation and the underlying mechanisms can vary widely among technologies and device types, it should be emphasized that the optimum values of temperature and design margin implied by this figure apply strictly to the device studied.

At any irradiation temperature considered, the amount of design margin required to bound low dose rate degradation decreases with measurement bias. The dependence of design margin on bias generally grows stronger as the irradiation temperature moves away from its range of optimum values.




Fig. 5. Relationship between irradiation temperature and design margin required to bound low dose rate degradation of the RF25 lateral pnp transistor. At any given irradiation temperature, the required design margin decreases with measurement bias.




Fig. 6. Effect of emitter-to-base voltage on the optimum temperature for enhanced radiation-induced gain degradation of the RF25 lateral pnp transistor. The optimum irradiation temperature decreases with measurement bias.

As shown in Fig. 6, the irradiation temperature corresponding to maximum degradation decreases from approximately 165°C at 0.5 V to approximately 150°C at 0.8 V. Larger design margins and smaller irradiation temperatures are required for hardness assurance testing at larger total doses[1,2]. The fact that the design margin and optimum irradiation temperature vary with measurement bias potentially complicates the development of a hardness assurance methodology for linear circuits. These trends suggest that design margins required to bound degradation of relevant circuit level parameters may be larger when the transistor is used for low power applications than when biased for optimum performance.

V. CONCLUSION

Enhanced low-dose-rate gain degradation of the ADI RF25 lateral pnp transistor was examined as a function of measurement bias. Degradation enhancement at low dose rates or elevated temperatures is more severe when measured at low emitter-to-base biases than when measured at high emitter-to-base biases. Mechanisms contributing to this bias dependence include interface trap charging, field effects from oxide trapped charge and emitter metallization, base series resistance and high-level carrier injection. As a result, larger design margins or higher irradiation temperatures are required to bound low-dose-rate degradation when the degradation is measured at low power.

ACKNOWLEDGMENTS

The authors are indebted to M. DeLaus and A. Martinez of Analog Devices, Inc. for furnishing the test devices. The authors acknowledge L. Cohn of the Defense Special Weapons

Agency and P. Winokur of Sandia National Laboratories for technical discussions of this work. Work performed at The Aerospace Corporation was supported by the U.S. Air Force Space and Missile Center under Contract No. F04701-93-C-0094. Work performed at Vanderbilt University and RLP Research, Inc. was supported by the Defense Special Weapons Agency. Sandia is a multiprogram laboratory operated by Sandia Corporation, a Lockheed Martin Company, for the U.S. Department of Energy under Contract No. DE-AC04-94AL85000.

REFERENCES

- [1] S. C. Witczak, R. D. Schrimpf, K. F. Galloway, D. M. Fleetwood, R. L. Pease, J. M. Puhl, D. M. Schmidt, W. E. Combs and J. S. Suehle, "Accelerated tests for simulating low dose rate gain degradation of lateral and substrate pnp bipolar junction transistors," *IEEE Trans. Nucl. Sci.*, vol. 43, pp. 3151-3160, 1996.
- [2] S. C. Witczak, R. D. Schrimpf, D. M. Fleetwood, K. F. Galloway, R. C. Lacoe, D. C. Mayer, J. M. Puhl, R. L. Pease and J. S. Suehle, "Hardness assurance testing of bipolar junction transistors at elevated irradiation temperatures," *IEEE Trans. Nucl. Sci.*, vol. 44, pp. 1989-2000, 1997.
- [3] R. L. Pease, S. McClure, J. Gorelick and S. C. Witczak, "Enhanced low-dose-rate sensitivity of a low-drop-out-voltage regulator," *IEEE Trans. Nucl. Sci.*, vol. 45, 1998.
- [4] D. M. Schmidt, A. Wu, R. D. Schrimpf, D. M. Fleetwood, R. L. Pease and W. E. Combs, "Modeling ionizing radiation induced gain degradation of the lateral pnp bipolar junction transistor," *IEEE Trans. Nucl. Sci.*, vol. 43, pp. 3032-3039, 1996.
- [5] A. H. Johnston, C. I. Lee and B. G. Rax, "Enhanced damage in bipolar devices at low dose rates: effects at very low dose rates," *IEEE Trans. Nucl. Sci.*, vol. 43, pp. 3049-3059, 1996.
- [6] K. O. P. Garone, C. Tsai, B. Scharf, M. Higgins, D. Mai, C. Kermerrac and J. Yasaitas, "A double-polysilicon self-aligned npn bipolar process (ADRF) with optional NMOS transistors for RF and microwave applications," *IEEE BCTM Tech. Dig.*, pp. 221-224, 1994.
- [7] D. M. Fleetwood, P. S. Winokur and J. R. Schwank, "Using laboratory x-ray and cobalt-60 irradiations to predict CMOS device response in strategic and space environments," *IEEE Trans. Nucl. Sci.*, vol. 35, pp. 1497-1505, 1988.
- [8] S. C. Witczak, R. C. Lacoe, D. C. Mayer, D. M. Fleetwood, R. D. Schrimpf and K. F. Galloway, "Space charge limited degradation of bipolar oxides at low electric fields," *IEEE Trans. Nucl. Sci.*, vol. 45, 1998.
- [9] C. T. Sah, R. N. Noyce and W. Shockley, "Carrier generation and recombination in p-n junction characteristics," *Proc. IRE*, vol. 45, pp. 1228-1243, 1957.
- [10] SILVACO International, ATLAS User Manual, Santa Clara, CA, 1998.
- [11] See, for example, S. M. Sze, *Physics of Semiconductor Devices*, New York: John Wiley & Sons, 1981, pp. 63-189.
- [12] H. J. Barnaby, R. D. Schrimpf, D. M. Fleetwood and S. L. Kosier, "The effects of emitter-tied field plates on lateral pnp ionizing radiation response," *IEEE BCTM Tech. Dig.*, pp. 35-38, 1998.

TECHNOLOGY OPERATIONS

The Aerospace Corporation functions as an "architect-engineer" for national security programs, specializing in advanced military space systems. The Corporation's Technology Operations supports the effective and timely development and operation of national security systems through scientific research and the application of advanced technology. Vital to the success of the Corporation is the technical staff's wide-ranging expertise and its ability to stay abreast of new technological developments and program support issues associated with rapidly evolving space systems. Contributing capabilities are provided by these individual Technology Centers:

Electronics Technology Center: Microelectronics, VLSI reliability, failure analysis, solid-state device physics, compound semiconductors, radiation effects, infrared and CCD detector devices, Micro-Electro-Mechanical Systems (MEMS), and data storage and display technologies; lasers and electro-optics, solid state laser design, micro-optics, optical communications, and fiber optic sensors; atomic frequency standards, applied laser spectroscopy, laser chemistry, atmospheric propagation and beam control, LIDAR/LADAR remote sensing; solar cell and array testing and evaluation, battery electrochemistry, battery testing and evaluation.

Mechanics and Materials Technology Center: Evaluation and characterization of new materials: metals, alloys, ceramics, polymers and composites; development and analysis of advanced materials processing and deposition techniques; nondestructive evaluation, component failure analysis and reliability; fracture mechanics and stress corrosion; analysis and evaluation of materials at cryogenic and elevated temperatures; launch vehicle fluid mechanics, heat transfer and flight dynamics; aerothermodynamics; chemical and electric propulsion; environmental chemistry; combustion processes; spacecraft structural mechanics, space environment effects on materials, hardening and vulnerability assessment; contamination, thermal and structural control; lubrication and surface phenomena; microengineering technology and microinstrument development.

Space and Environment Technology Center: Magnetospheric, auroral and cosmic ray physics, wave-particle interactions, magnetospheric plasma waves; atmospheric and ionospheric physics, density and composition of the upper atmosphere, remote sensing, hyperspectral imagery; solar physics, infrared astronomy, infrared signature analysis; effects of solar activity, magnetic storms and nuclear explosions on the earth's atmosphere, ionosphere and magnetosphere; effects of electromagnetic and particulate radiations on space systems; component testing, space instrumentation; environmental monitoring, trace detection; atmospheric chemical reactions, atmospheric optics, light scattering, state-specific chemical reactions and radiative signatures of missile plumes, and sensor out-of-field-of-view rejection.